

### **TECHNICAL SPECIFICATION**

# Rotary switches LW26-Q



### **Description:**

The rotary switches LW26 series are produced for switching on/off electrical circuits with commutated current from 20 to 160A. They are designed on the bases of the rotor-eccentric switching on which is realized through turning of the handle to 60 or 90 degrees. The normal operation is used for commutation of two, three or four conductor systems. There are special rotary switches that switch on under given connection schemes and are used to control motors, electric welding machines and other consumers.

#### **Technical data:**

• Power supply voltage: 230/400V; 50Hz

Number of levels: 2

• Number of positions: 2

Insulation voltage: 690V

• Impulse voltage withstand: 6 000V

• Mechanical wear resistance: 3x10<sup>5</sup> commutation cycles

• Operating temperature: -10°C - +50°C

• Humidity: 35 - 85%RH

Commutation capacity: 20-160A

Resistant to UV rays plastic

• Cable connection: screw joining


• Maximum section of the power supply conductors: 50.0mm2





# Mounting:

- directly to the control panel
- thickness of the surface to which it is mounted: max 5mm

# **Dimensions:**







Туре	Front panel	Joining	Overall dimensions (mm)				Mounting dimensions (mm)			
		conductor (mm²)	Α	В	С	L	а	b	d1	d2
LW26-20	M1 panel	1x2.5	48	46	43	22+9.6n	36	36	Ø8.5	Ø4.5
	M1 panel with inscription field		48	60	43	22+9.6n	36	36	Ø8.5	Ø4.5
LW26-25	M1 panel	1x4.0	48	48	45. 2	23+12.8n	36	36	Ø8.5	Ø4.5
LW26-32	M2 panel	1x6.0	64	64	58	29.2+12.8n	48	48	Ø10	Ø4.5
LW26-63	M2 panel	1x16	64	64	66	29.2+21.5n	48	48	Ø10	Ø4.5
LW26-125	M3 panel	1x35	88	88	84	35+26.5n	68	68	Ø13	Ø6
LW26-160	M3 panel	1x50	88	88	88	35+32.5n	68	68	Ø13	Ø6

<sup>\*</sup>n – number of modules



# **Variants:**

Туре	Scheme	In (A)	Levels	Packing / Box	Catalogue number
				(pcs)	
LW26-10Q		10	2	1/100	492101
LW26-16Q	Q10	16	2	1/100	492161
LW26-20Q	three-poles switching on;	20	2	1/100	492201
LW26-25Q	motor starting and stopping;	25	2	1 / 100	492251
LW26-32Q	voltage turning on/off to the	32	2	1 / 72	492321
LW26-63Q	consumers	63	2	1 / 64	492631
LW26-125Q		125	2	1 / 24	492951
LW26-160Q		160	2	1 / 27	492961

### **Standards:**

EN 60947-1

EN 60947-3-1



